



## NTE1395 Integrated Circuit Dual Audio Power Amplifier, 5.8W/Ch

### **Features:**

- Very Low Distortion
- Easy to Mount
- Overvoltage Handling Capability up to 50V for 200ms
- Thermal Shut-Down Circuit Included
- Fewer Number of External Components Required

**Absolute Maximum Ratings:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Operating Supply Voltage	.....	18V
DC Supply Voltage (30sec)	.....	26V
Peak Supply Voltage (Note 1)	.....	50V
Output Current (Per Channel)	.....	4A
Power Dissipation (Per Package)	.....	15W
Operating Temperature Range, $T_{opr}$	.....	$-20^\circ$ to $+70^\circ\text{C}$
Storage Temperature Range, $T_{stg}$	.....	$-55^\circ$ to $+125^\circ\text{C}$
Junction Temperature, $T_J$	.....	$+150^\circ\text{C}$
Thermal Resistance, Junction-to-Case, $R_{thJC}$	.....	3°C/W

Note 1. Pulse width = 200ms,  $T_{rise} \geq 1\text{ms}$

**Electrical Characteristics:** ( $T_A = +25^\circ\text{C}$ ,  $V_{CC} = 13.2\text{V}$ ,  $f = 1\text{kHz}$ ,  $R_L = 4\Omega$ , One-Half Operation unless otherwise specified)

Parameter	Symbol	Test Conditions		Min	Typ	Max	Unit
Quiescent Current	$I_Q$	$V_{in} = 0$		40	80	160	mA
Input Bias Voltage	$V_B$	$V_{in} = 0$		—	—	40	mV
Voltage Gain	$G_V$	$V_{in} = 2.45\text{mV}$		45	47	49	dB
Difference of Voltage Gain	$\Delta G_V$	$V_{in} = 2.45\text{mV}$		—	—	$\pm 1.5$	dB
Output Power Per Channel	$P_{out}$	$R_L = 4\Omega$ , $\text{THD} = 10\%$	$V_{CC} = 13.2\text{V}$	5.0	5.8	—	W
			$V_{CC} = 14.4\text{V}$	—	7.0	—	W
Total Harmonic Distortion	$\text{THD}$	$P_{out} = 1.5\text{W}$		—	0.08	0.5	%
Noise Output	$\text{WBN}$	$R_g = 10\text{k}\Omega$ , $\text{BW} = 20\text{Hz}$ to $20\text{kHz}$		—	0.4	1.0	mV
Supply Voltage Rejection Ratio	$\text{SVR}$	$R_g = 600\Omega$ , $f = 500\text{Hz}$		36	46	—	dB
Input Resistance	$R_{in}$	$f = 1\text{kHz}$		—	30	—	k $\Omega$
Rolloff Frequency	$f_l$	$G_V = 3\text{dB}$ from $f = 1\text{kHz}$ Ref	Low	—	40	—	Hz
	$f_h$		High	—	60	—	kHz
Crosstalk	$\text{CT}$	$f = 500\text{Hz}$ , $R_g = 600\Omega$		40	60	—	dB

**Pin Connection Diagram**  
(Front View)

