

Power Transistor (–80V, –1A)

2SB1260 / 2SB1181 / 2SB1241


●Features

- 1) High breakdown voltage and high current.
 $BV_{CEO} = -80V$, $I_C = -1A$
 - 2) Good h_{FE} linearity.
 - 3) Low $V_{CE(sat)}$.
- Complements the 2SD1898 / 2SD1863 / 2SD1733.

●Structure

Epitaxial planar type
 PNP silicon transistor

●Dimensions (Unit : mm)



* Denotes h_{FE}

●Absolute maximum ratings (Ta=25°C)

Parameter		Symbol	Limits	Unit
Collector-base voltage		V_{CBO}	–80	V
Collector-emitter voltage		V_{CEO}	–80	V
Emitter-base voltage		V_{EBO}	–5	V
Collector current		I_C	–1	A (DC)
		I_{CP}	–2 *1	A (Pulse)
Collector power dissipation	2SB1260	P_C	0.5	W
	2SB1241, 2SB1181		2 *2	
	2SB1241		1 *3	
	2SB1181		10	W (Tc=25°C)
Junction temperature		T_j	150	°C
Storage temperature		T_{stg}	–55 to 150	°C

*1 2SB1260 : $P_W=20ms$ duty=1/2

2SB1241 : Single pulse, $P_W=100ms$

*2 2SB1260 : When mounted on a 40×40×0.7 mm ceramic board.

*3 2SB1241 : Printed circuit board, 1.7mm thick, collector copper plating 100mm² or larger.

●Electrical characteristics (Ta=25°C)

Parameter		Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector-base breakdown voltage		BV_{CBO}	−80	−	−	V	$I_C = -50\mu A$
Collector-emitter breakdown voltage		BV_{CEO}	−80	−	−	V	$I_C = -1mA$
Emitter-base breakdown voltage		BV_{EBO}	−5	−	−	V	$I_E = -50\mu A$
Collector cutoff current		I_{CBO}	−	−	−1	μA	$V_{CB} = -60V$
Emitter cutoff current		I_{EBO}	−	−	−1	μA	$V_{EB} = -4V$
Collector-emitter saturation voltage		$V_{CE(sat)}$	−	−	−0.4	V	$I_C/I_B = -500mA/-50mA$
DC current transfer ratio	2SB1260, 2SB1181	h_{FE}	82	−	390	−	$V_{CE} = -3V, I_C = -0.1A$
	2SB1241		120	−	390	−	
Transition frequency	2SB1181	f_T	−	100	−	MHz	$V_{CE} = -10V, I_E = 50mA, f = 100MHz$
Output capacitance	2SB1260	C_{ob}	−	20	−	pF	$V_{CB} = -10V$ $I_E = 0A$
	2SB1181, 2SB1241		−	25	−	pF	$f = 1MHz$

●Packaging specifications and h_{FE}

Type	h_{FE}	Package	Taping		
		Code	TL	TV2	T100
		Basic ordering unit (pieces)	2500	2500	1000
2SB1260	PQR		-	-	○
2SB1241	QR		-	○	-
2SB1181	PQR		○	-	-

h_{FE} values are classified as follows :

Item	P	Q	R
h_{FE}	82 to 180	120 to 270	180 to 390

●Electrical characteristic curves




Fig.1 Ground Emitter Output Characteristics




Fig.2 Grounded Emitter Propagation Characteristics




Fig.3 DC Current Gain vs Collector Current




Fig.4 Collector-Emitter Saturation Voltage vs Collector Current




Fig.5 Transition Frequency vs Emitter Current




Fig.6 Emitter Input Capacitance vs. Emitter-Base Voltage
Collector Output Capacitance vs. Collector-Base

Notes

No copying or reproduction of this document, in part or in whole, is permitted without the consent of ROHM Co.,Ltd.

The content specified herein is subject to change for improvement without notice.

The content specified herein is for the purpose of introducing ROHM's products (hereinafter "Products"). If you wish to use any such Product, please be sure to refer to the specifications, which can be obtained from ROHM upon request.

Examples of application circuits, circuit constants and any other information contained herein illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production.

Great care was taken in ensuring the accuracy of the information specified in this document. However, should you incur any damage arising from any inaccuracy or misprint of such information, ROHM shall bear no responsibility for such damage.

The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM and other parties. ROHM shall bear no responsibility whatsoever for any dispute arising from the use of such technical information.

The Products specified in this document are intended to be used with general-use electronic equipment or devices (such as audio visual equipment, office-automation equipment, communication devices, electronic appliances and amusement devices).

The Products specified in this document are not designed to be radiation tolerant.

While ROHM always makes efforts to enhance the quality and reliability of its Products, a Product may fail or malfunction for a variety of reasons.

Please be sure to implement in your equipment using the Products safety measures to guard against the possibility of physical injury, fire or any other damage caused in the event of the failure of any Product, such as derating, redundancy, fire control and fail-safe designs. ROHM shall bear no responsibility whatsoever for your use of any Product outside of the prescribed scope or not in accordance with the instruction manual.

The Products are not designed or manufactured to be used with any equipment, device or system which requires an extremely high level of reliability the failure or malfunction of which may result in a direct threat to human life or create a risk of human injury (such as a medical instrument, transportation equipment, aerospace machinery, nuclear-reactor controller, fuel-controller or other safety device). ROHM shall bear no responsibility in any way for use of any of the Products for the above special purposes. If a Product is intended to be used for any such special purpose, please contact a ROHM sales representative before purchasing.

If you intend to export or ship overseas any Product or technology specified herein that may be controlled under the Foreign Exchange and the Foreign Trade Law, you will be required to obtain a license or permit under the Law.



Thank you for your accessing to ROHM product informations.
More detail product informations and catalogs are available, please contact us.

ROHM Customer Support System

<http://www.rohm.com/contact/>