


## BC327/328

BC327/328

### Switching and Amplifier Applications

- Suitable for AF-Driver stages and low power output stages
- Complement to BC337/BC338



### PNP Epitaxial Silicon Transistor

#### Absolute Maximum Ratings $T_a=25^\circ\text{C}$ unless otherwise noted

Symbol	Parameter	Value	Units
$V_{CES}$	Collector-Emitter Voltage		
	: BC327	-50	V
	: BC328	-30	V
$V_{CEO}$	Collector-Emitter Voltage		
	: BC327	-45	V
	: BC328	-25	V
$V_{EBO}$	Emitter-Base Voltage	-5	V
$I_C$	Collector Current (DC)	-800	mA
$P_C$	Collector Power Dissipation	625	mW
$T_J$	Junction Temperature	150	$^\circ\text{C}$
$T_{STG}$	Storage Temperature	-55 ~ 150	$^\circ\text{C}$

#### Electrical Characteristics $T_a=25^\circ\text{C}$ unless otherwise noted

Symbol	Parameter	Test Condition	Min.	Typ.	Max.	Units
$BV_{CEO}$	Collector-Emitter Breakdown Voltage	$I_C = -10\text{mA}, I_B = 0$	-45			V
			-25			V
$BV_{CES}$	Collector-Emitter Breakdown Voltage	$I_C = -0.1\text{mA}, V_{BE} = 0$	-50			V
			-30			V
$BV_{EBO}$	Emitter-Base Breakdown Voltage	$I_E = -10\mu\text{A}, I_C = 0$	-5			V
$I_{CES}$	Collector Cut-off Current	$V_{CE} = -45\text{V}, V_{BE} = 0$ $V_{CE} = -25\text{V}, V_{BE} = 0$		-2	-100	nA
				-2	-100	nA
$h_{FE1}$	DC Current Gain	$V_{CE} = -1\text{V}, I_C = -100\text{mA}$ $V_{CE} = -1\text{V}, I_C = -300\text{mA}$	100		630	
$h_{FE2}$			40			
$V_{CE}(\text{sat})$	Collector-Emitter Saturation Voltage	$I_C = -500\text{mA}, I_B = -50\text{mA}$			-0.7	V
$V_{BE}(\text{on})$	Base-Emitter On Voltage	$V_{CE} = -1\text{V}, I_C = -300\text{mA}$			-1.2	V
$f_T$	Current Gain Bandwidth Product	$V_{CE} = -5\text{V}, I_C = -10\text{mA}, f = 20\text{MHz}$		100		MHz
$C_{ob}$	Output Capacitance	$V_{CB} = -10\text{V}, I_E = 0, f = 1\text{MHz}$		12		pF

### $h_{FE}$ Classification

Classification	16	25	40
$h_{FE1}$	100 ~ 250	160 ~ 400	250 ~ 630
$h_{FE2}$	60-	100-	170-

# Typical Characteristics




Figure 1. Static Characteristic




Figure 2. Static Characteristic




Figure 3. DC current Gain




Figure 4. Base-Emitter Saturation Voltage  
Collector-Emitter Saturation Voltage




Figure 5. Base-Emitter On Voltage





Figure 6. Gain Bandwidth Product

# Package Dimensions

## TO-92



Dimensions in Millimeters

## TRADEMARKS

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACE <sup>™</sup>	FACT <sup>™</sup>	ImpliedDisconnect <sup>™</sup>	PACMAN <sup>™</sup>	SPM <sup>™</sup>
ActiveArray <sup>™</sup>	FACT Quiet series <sup>™</sup>	ISOPLANAR <sup>™</sup>	POP <sup>™</sup>	Stealth <sup>™</sup>
Bottomless <sup>™</sup>	FAST <sup>®</sup>	LittleFET <sup>™</sup>	Power247 <sup>™</sup>	SuperSOT <sup>™</sup> -3
CoolFET <sup>™</sup>	FAST <sup>r</sup> <sup>™</sup>	MicroFET <sup>™</sup>	PowerTrench <sup>®</sup>	SuperSOT <sup>™</sup> -6
CROSSVOLT <sup>™</sup>	FRFET <sup>™</sup>	MicroPak <sup>™</sup>	QFET <sup>™</sup>	SuperSOT <sup>™</sup> -8
DOME <sup>™</sup>	GlobalOptoisolator <sup>™</sup>	MICROWIRE <sup>™</sup>	QS <sup>™</sup>	SyncFET <sup>™</sup>
EcoSPARK <sup>™</sup>	GTO <sup>™</sup>	MSX <sup>™</sup>	QT Optoelectronics <sup>™</sup>	TinyLogic <sup>™</sup>
E <sup>2</sup> CMOS <sup>™</sup>	HiSeC <sup>™</sup>	MSXPro <sup>™</sup>	Quiet Series <sup>™</sup>	TruTranslation <sup>™</sup>
EnSigna <sup>™</sup>	I <sup>2</sup> C <sup>™</sup>	OCX <sup>™</sup>	RapidConfigure <sup>™</sup>	UHC <sup>™</sup>
Across the board. Around the world. <sup>™</sup>		OCXPro <sup>™</sup>	RapidConnect <sup>™</sup>	UltraFET <sup>®</sup>
The Power Franchise <sup>™</sup>		OPTOLOGIC <sup>®</sup>	SILENT SWITCHER <sup>®</sup>	VCX <sup>™</sup>
Programmable Active Droop <sup>™</sup>		OPTOPLANAR <sup>™</sup>	SMART START <sup>™</sup>	

## DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

## LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.
2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

## PRODUCT STATUS DEFINITIONS

### Definition of Terms

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.

Home >> Find products >>

## BC327

PNP Epitaxial Silicon Transistor

### Contents

- [Features](#)
- [Applications](#)
- [Product status/pricing/packaging](#)
- [Order Samples](#)

• [Qualification Support](#)

### Features

- Suitable for AF-Driver stages and low power output stages
- Complement to BC337/BC338

[back to top](#)

### Applications

#### Switching and Amplifier

[back to top](#)

[Product status/pricing/packaging](#)

**BUY**

**BUY**

### Datasheet

[Download this datasheet](#)



[e-mail this datasheet](#)



### This page

[Print version](#)

### Related Links

[Request samples](#)

[How to order products](#)

[Product Change Notices \(PCNs\)](#)

[Support](#)

[Sales support](#)

[Quality and reliability](#)

[Design center](#)

Product	Product status	Pb-free Status	Pricing*	Package type	Leads	Packing method	Package Marking Convention**
BC327	Full Production	Full Production	\$0.079	<a href="#">TO-92</a>	3	BULK	Line 1: \$Y (Fairchild logo) &Z (Asm. Plant Code) &3 (3-Digit Date Code) Line 2: BC327
BC32716	Full Production	Full Production	\$0.079	<a href="#">TO-92</a>	3	BULK	Line 1: \$Y (Fairchild logo) &Z (Asm. Plant Code) &3 (3-Digit Date Code) Line 2: BC327 Line 3: -16
BC32716BU	Full Production		\$0.0296	<a href="#">TO-92</a>	3	BULK	Line 1: BC327 Line 2: 16 Line 3: -&3

							
BC32716TA	Full Production		\$0.0296	<a href="#">TO-92</a>	3	AMMO	Line 1: BC327 Line 2: 16 Line 3: -&3
BC32716TAR	Full Production		\$0.0296	<a href="#">TO-92</a>	3	AMMO	Line 1: BC327 Line 2: 16 Line 3: -&3
BC32716TF	Full Production		\$0.0296	<a href="#">TO-92</a>	3	TAPE REEL	Line 1: BC327 Line 2: 16 Line 3: -&3
BC32716TFR	Full Production		\$0.0296	<a href="#">TO-92</a>	3	TAPE REEL	Line 1: BC327 Line 2: 16 Line 3: -&3
BC32725	Full Production		\$0.079	<a href="#">TO-92</a>	3	BULK	Line 1: \$Y (Fairchild logo) &Z (Asm. Plant Code) &3 (3-Digit Date Code) Line 2: BC327 Line 3: -25
BC32725BU	Full Production		\$0.0296	<a href="#">TO-92</a>	3	BULK	Line 1: BC327 Line 2: 25 Line 3: -&3
BC32725TA	Full Production		\$0.0296	<a href="#">TO-92</a>	3	AMMO	Line 1: BC327 Line 2: 25 Line 3: -&3
BC32725TAR	Full Production		\$0.0296	<a href="#">TO-92</a>	3	AMMO	Line 1: BC327 Line 2: 25 Line 3: -&3
BC32725TF	Full Production		\$0.0296	<a href="#">TO-92</a>	3	TAPE REEL	Line 1: BC327 Line 2: 25 Line 3: -&3
BC32725TFR	Full Production		\$0.0296	<a href="#">TO-92</a>	3	TAPE REEL	Line 1: BC327 Line 2: 25 Line 3: -&3

BC32725_J18Z	Full Production		N/A	<a href="#">TO-92</a>	3	BULK	Line 1: <b>\$Y</b> (Fairchild logo) & <b>Z</b> (Asm. Plant Code) & <b>3</b> (3-Digit Date Code) Line 2: BC327 Line 3: -25
BC32740BU	Full Production		\$0.0296	<a href="#">TO-92</a>	3	BULK	Line 1: BC327 Line 2: 40 Line 3: -&3
BC32740TA	Full Production		\$0.0296	<a href="#">TO-92</a>	3	AMMO	Line 1: BC327 Line 2: 40 Line 3: -&3
BC327ABU	Full Production		\$0.0296	<a href="#">TO-92</a>	3	BULK	Line 1: BC327 Line 3: -&3
BC327BU	Full Production		\$0.0296	<a href="#">TO-92</a>	3	BULK	Line 1: BC327 Line 3: -&3
BC327TA	Full Production		\$0.0296	<a href="#">TO-92</a>	3	AMMO	Line 1: BC327 Line 3: -&3
BC327TAR	Full Production		\$0.0296	<a href="#">TO-92</a>	3	AMMO	Line 1: BC327 Line 3: -&3
BC327TF	Full Production		\$0.0296	<a href="#">TO-92</a>	3	TAPE REEL	Line 1: BC327 Line 3: -&3
BC327TFR	Full Production		\$0.0296	<a href="#">TO-92</a>	3	TAPE REEL	Line 1: BC327 Line 3: -&3
BC327_NL	Full Production		N/A	<a href="#">TO-92</a>	3	BULK	Line 1: <b>\$Y</b> (Fairchild logo) & <b>Z</b> (Asm. Plant Code) & <b>3</b> (3-Digit Date Code) Line 2: BC327

\* Fairchild 1,000 piece Budgetary Pricing

\*\* A sample button will appear if the part is available through Fairchild's on-line samples program. If there is no sample button, please contact a [Fairchild distributor](#) to obtain samples



Indicates product with Pb-free second-level interconnect. For more information [click here](#).

Package marking information for product BC327 is available. [Click here for more information](#).

[back to top](#)

### Qualification Support

Click on a product for detailed qualification data

Product
<a href="#">BC327</a>
<a href="#">BC32716</a>
<a href="#">BC32716BU</a>
<a href="#">BC32716TA</a>
<a href="#">BC32716TAR</a>
<a href="#">BC32716TF</a>
<a href="#">BC32716TFR</a>
<a href="#">BC32725</a>
<a href="#">BC32725BU</a>
<a href="#">BC32725TA</a>
<a href="#">BC32725TAR</a>
<a href="#">BC32725TF</a>
<a href="#">BC32725TFR</a>
<a href="#">BC32725_J18Z</a>
<a href="#">BC32740BU</a>
<a href="#">BC32740TA</a>
<a href="#">BC327ABU</a>
<a href="#">BC327BU</a>
<a href="#">BC327TA</a>
<a href="#">BC327TAR</a>
<a href="#">BC327TF</a>
<a href="#">BC327TFR</a>
<a href="#">BC327_NL</a>

[back to top](#)

© 2007 Fairchild Semiconductor

[Products](#) | [Design Center](#) | [Support](#) | [Company News](#) | [Investors](#) | [My Fairchild](#) | [Contact Us](#) | [Site Index](#) | [Privacy Policy](#) | [Site Terms & Conditions](#) | [Standard Terms & Conditions](#) | [Legal](#)