WORLD-BEAM[®] QS18LD Laser Diffuse Series Sensors



Datasheet



- Visible Class 1 laser for diffuse sensing
- Narrow effective beam provides small-object detection and precise position control
- Crosstalk rejection algorithm protects against optical disturbance from adjacent sensors
- Excellent optical performance throughout sensing range, even close up
- 10 to 30 V dc operation, with complementary (SPDT) NPN or PNP outputs, depending on model
- Bright LED operating status indicators are visible from 360°
- Compact, rugged sealed housing, protected circuitry
- Mounting versatility popular 18 mm threaded barrel or side-mount
- Choose 2 m (6.5 ft) or 9 m (30 ft) cable or one of four QD options

Models	Sensing Range	Spot Size at Focus	Cable	Output
QS18VN6LD	650 nm Visible Red Class 1 Laser 300 mm (12 in)	Approximately 1 mm at 300 mm (0.039 in at 12 in)	4-wire, 2 m (6.5 ft) integral cable	NPN
QS18VP6LD				PNP

The standard 2 m (6.5 ft) cable models are listed. To order the 9 m (30 ft) cable models, add the suffix "W/30" to the model number (e.g., QS18VN6LD W/30). A model with a QD connector requires a mating cordset. To order the QD models:

- For 4-pin integral Euro-style QD, add suffix "Q8" (e.g., QS18VN6LDQ8).
- For 4-pin integral Pico-style QD, add suffix "Q7" (e.g., QS18VN6LDQ7).
- For 4-pin Euro-style 150 mm (6 inch) pigtail QD, add suffix "Q5" (e.g., QS18VN6LDQ5).
- For 4-pin Pico-style 150 mm (6 inch) pigtail QD, add suffix "Q" (e.g., QS18VN6LDQ).



WARNING: Not To Be Used for Personnel Protection

Never use this device as a sensing device for personnel protection. Doing so could lead to serious injury or death. This device does not include the self-checking redundant circuitry necessary to allow its use in personnel safety applications. A sensor failure or malfunction can cause either an energized or de-energized sensor output condition.

Wiring Diagrams



Cabled wiring diagrams are shown. Quick disconnect (QD) wiring diagrams are functionally identical.

Description of Laser Classes

Class 1 Lasers

Class 1 lasers are lasers that are safe under reasonably foreseeable conditions of operation, including the use of optical instruments for intrabeam viewing.

Reference IEC 60825-1:2001, Section 8.2.

Class 1 Laser Characteristics: See Specifications.



CAUTION: Do Not Disassemble for Repair

This device contains no user-serviceable components. Do not attempt to disassemble for repair. Use of controls or adjustments or performance of procedures other than those specified herein may result in hazardous radiation exposure. A defective unit must be returned to the manufacturer. CLASS 1 LASER PRODUCT Complies with 21 CFR 1040.10 and 1040.11 except for deviations pursuant to Laser Notice No. 50, dated 7-26-01.

For Safe Laser Use (Class 1 or Class 2):

- Do not stare at the laser.
- Do not point the laser at a person's eye.
- · Mount open laser beam paths either above or below eye level, where practical.
- · Terminate the beam emitted by the laser product at the end of its useful path.

Specifications

Supply Voltage Repeatability 10 to 30 V dc (10% maximum ripple) at less than 15 mA, exclusive of 130 microseconds load Sensing Hysteresis Sensing Beam 15% of range typical Visible red LED, 650 nm Adjustments Laser Characteristics Single-turn sensitivity (Gain) adjustment potentiometer Wavelength: 650 nm visible red Class 1 laser Indicators Pulse Width: 7 microseconds 2 LED indicators on sensor top: Rep Rate: 130 microseconds Green solid: Power on Average Output Power: 0.065 mW Amber solid: Light sensed Supply Protection Circuitry Amber flashing: Marginal excess gain (1 to 1.5x excess gain) Protected against reverse polarity and transient voltages Construction **Output Configuration** ABS housing, acrylic lens cover, 3 mm mounting hardware included Solid-state complementary (SPDT): NPN or PNP (current sinking or Environmental Ratings sourcing), depending on model; IEC IP67; NEMA 6; UL Type 1 Rating: 100 mA maximum each output at 25 °C Connections Off-state leakage current: 2 m (6.5 ft) 4-wire PVC cable 9 m (30 ft) 4-wire PVC cable 4-pin Pico-NPN: less than 200 µA @ 30 V dc (See Application Note 1) style or Euro-style QD, 4-pin Pico-style or Euro-style 150 mm (6 in) PNP: less than 10 µA @ 30 V dc pigtail QD, depending on model ON-state saturation voltage: **Operating Conditions** NPN: less than 1.6 V @ 100 mA Temperature: -10 °C to 50 °C (14 °F to 122 °F) PNP: less than 3.0 V @ 100 mA Relative Humidity: 90% @ 50 °C (non-condensing) **Output Protection Circuitry** Protected against false pulse on power-up and continuous overload or Laser Classification Class 1 laser product; Complies with IEC 60825-1:2001 and 21 CFR short circuit of outputs 1040.10, except for deviations pursuant to Laser Notice 50, dated Output Response 7-26-01 700 microseconds ON/OFF Application Notes NOTE: 200 millisecond delay on power-up; outputs do not conduct . NPN off-state leakage current is < 200 μ A for load resistances > 3 k Ω during this time or optically isolated loads. For load current of 100 mA, leakage is < 1% of load current. Certifications



Performance Curves

Performance is based on a 90% reflectance white test card.



Dimensions

All measurements are listed in millimeters (inches).

Cabled Models



Locknut (included with all models)





UQ

150 mm (6") Pico-style Pigtail

Pico-Style QD Models

41.5 m (1.63"

> 4-pin Pico-Style QD



150 mm (6") Euro-style Pigtail Euro-Style QD Models

49 mm (1.93")

> 4-pin Euro-Style QD

M3 Hardware Packet Contents:

- 2 M3 x 0.5 x 20 mm SS Screw
 - 2 M3 x 0.5 SS Hex Nut
 - 2 M3 SS Washer

Accessories

4-Pin Snap-on M8/Pico-Style Cordsets						
Model	Length	Style	Dimensions	Pinout		
PKG4-2	2.00 m (6.56 ft)	Straight		4		
PKW4Z-2	2.00 m (6.56 ft)	Right-Angle	φ 10.9 → ↓ φ 10.9 → ↓	1 = Brown 2 = White 3 = Blue 4 = Black		









Banner Engineering Corp Limited Warranty

Banner Engineering Corp. warrants its products to be free from defects in material and workmanship for one year following the date of shipment. Banner Engineering Corp. will repair or replace, free of charge, any product of its manufacture which, at the time it is returned to the factory, is found to have been defective during the warranty period. This warranty does not cover damage or liability for misuse, abuse, or the improper application or installation of the Banner product.

THIS LIMITED WARRANTY IS EXCLUSIVE AND IN LIEU OF ALL OTHER WARRANTIES WHETHER EXPRESS OR IMPLIED (INCLUDING, WITHOUT LIMITATION, ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE), AND WHETHER ARISING UNDER COURSE OF PERFORMANCE, COURSE OF DEALING OR TRADE USAGE.

This Warranty is exclusive and limited to repair or, at the discretion of Banner Engineering Corp., replacement. IN NO EVENT SHALL BANNER ENGINEERING CORP. BE LIABLE TO BUYER OR ANY OTHER PERSON OR ENTITY FOR ANY EXTRA COSTS, EXPENSES, LOSSES, LOSS OF PROFITS, OR ANY INCIDENTAL, CONSEQUENTIAL OR SPECIAL DAMAGES RESULTING FROM ANY PRODUCT DEFECT OR FROM THE USE OR INABILITY TO USE THE PRODUCT, WHETHER ARISING IN CONTRACT OR WARRANTY, STATUTE, TORT, STRICT LIABILITY, NEGLIGENCE, OR OTHERWISE.

Banner Engineering Corp. reserves the right to change, modify or improve the design of the product without assuming any obligations or liabilities relating to any product previously manufactured by Banner Engineering Corp.

