## DC axial fans

### □ 25 x 8 mm



Material: Housing: GRP<sup>1)</sup> (PBT)

Impeller: GRP<sup>1)</sup> (PA)

Direction of air flow: Exhaust over strutsDirection of rotation: Counter-clockwise, seen

on rotor

Connection: Via single wires AWG 28,


TR 64

**– Mass:** 5 g


1) Fibreglass-reinforced plastic

Series 250 with Speed Signal /2			voltage	e.	pressure level	power level	e bearings s		peq	range	L <sub>10</sub> (20 °C) Standard L <sub>10</sub> (60 °C) Standard	incy L <sub>10IPC</sub> page 17	
Nominal data	Air flow	Air flow	Nominal vo	Voltage range	Sound press	Sound powe	Sintec sleeve Ball bearings	Input power	Nominal speed	Temperature range	Service life L <sub>1</sub> ebm-papst St Service life L <sub>1</sub> ebm-papst St	Life expectancy (40 °C) see page	Curve
Туре	m³/h	cfm	VDC	VDC	dB(A)	Bel(A)	■/■	Watts	rpm	°C	Hours	Hours	
"													
255 /2N	3,5	1,9	5	4,55,5	16	< 3	-	0,4	9 600	-10+70	40 000 / 15 000	42 500	2
		_	5 5					_			40 000 / 15 000 35 000 / 15 000*	42 500 37 500	3
255 /2N	3,5	1,9		4,55,5	16	< 3	_	0,4	9 600	-10+70			

\* at 55 °C



Air performance measured as per: ISO 5801, Installation category A, without accidental contact. Noise: Total sound power level  $L_{\rm pA}$  ISO 103002 measured on half-sphere of 2 m; Sound pressure level  $L_{\rm pA}$  measured at 1 m distance to fan axis. The acoustic values are only valid for the described measurement set-up and may vary depending on the installation situation. In case of any deviation to the standard setup, the values have to be checked and reviewed once installed or fitted. For detailed information see http://www.ebmpapst.com/general conditions






# Speed signal /2



- Speed-proportional square-wave signal for external speed monitoring of fan motor
- 2 pulses per revolution
- Open collector signal output
- Extremely wide operating voltage range
- Easy adaptation to user interface
- Connection via separate lead
- The sensor signal also serves as a major comparison variable for setting and maintaining the setpoint speed for interactive or controlled cooling with one or several interconnected fans.


### **Electrical connection**



All voltages measured to ground. External load resistor  $\rm R_{\mbox{\scriptsize R}}$  /  $\rm U_{\mbox{\scriptsize S}}$  /  $\rm U_{\mbox{\scriptsize BS}}$  required.

#### Signal output voltage

Standard signal for all models (exceptions see below)



Signal data	Speed signal US Low	Condition: Isink	Speed signal US High	Condition: Isource	Sensor operating voltage UBS max.	Perm. sink current Isink max.	Pulses per revolution	Fan description Basic type	
Туре	VDC	mA	VDC	mA	VDC	mA		Page	
250	≤ 0,4	2	≤ 30	0	30	2	2	31	
Subject to alterations									