
SDFS018D - D2932, MARCH 1987 - REVISED OCTOBER 1993

- Contains Eight D-Type Flip-Flops With Single-Rail Outputs
- Clock Enable Latched to Avoid False Clocking
- Applications Include:

 Buffer/Storage Registers
 Shift Registers
 Pattern Generators
- Buffered Common Enable Input
- Package Options Include Plastic Small-Outline Packages and Standard Plastic 300-mil DIPs



description

The SN74F377A is a monolithic, positive-edge-triggered, octal, D-type flip-flop with clock enable inputs. The SN74F377A features a latched clock enable (CE) input.

Information at the data (D) inputs meeting the setup time requirements is transferred to the Q outputs on the positive-going edge of the clock pulse if $\overline{\text{CE}}$ is low. Clock triggering occurs at a particular voltage level and is not directly related to the positive-going pulse. When the clock input is at either the high or low level, the D input signal has no effect at the output. The circuits are designed to prevent false clocking by transitions at the $\overline{\text{CE}}$ input.


The SN74F377A is characterized for operation from 0°C to 70°C.

FUNCTION TABLE (each flip-flop)

INPUTS			OUTPUT
CE	CLK	D	Q
Н	Х	Х	Q ₀
L	\uparrow	Н	Н
L	\uparrow	L	L
Х	L	Χ	Q ₀




logic symbol[†]



[†]This symbol is in accordance with ANSI/IEEE Std 91-1984 and IEC Publication 617-12.

logic diagram (positive logic)



To Seven Other Channels

absolute maximum ratings over operating free-air temperature range (unless otherwise noted)‡

Supply voltage range, V _{CC}	\ldots -0.5 V to 7 V
Input voltage range, V _I (see Note 1)	$-1.2\ V$ to 7 V
Input current range	\dots -30 mA to 5 mA
Voltage range applied to any output in the high state	\dots -0.5 V to V _{CC}
Current into any output in the low state	40 mA
Operating free-air temperature range	0° C to 70° C
Storage temperature range	65°C to 150°C

[‡] Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

NOTE 1: The input-voltage ratings may be exceeded provided the input-current ratings are observed.



recommended operating conditions

		MIN	NOM	MAX	UNIT
Vcc	Supply voltage	4.5	5	5.5	V
VIH	High-level input voltage	2			V
V _{IL}	Low-level input voltage			0.8	V
liK	Input clamp current			- 18	mA
I _{OH}	High-level output current			- 1	mA
lOL	Low-level output current			20	mA
TA	Operating free-air temperature	0		70	°C

electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

PARAMETER	TEST CONDITIONS			TYP†	MAX	UNIT
Vou	$V_{CC} = 4.5 \text{ V},$	$I_{OH} = -1 \text{ mA}$	2.5	3.4		V
VOH	$V_{CC} = 4.75 V$,	$I_{OH} = -1 \text{ mA}$	2.7			V
V _{OL}	$V_{CC} = 4.5 \text{ V},$	$I_{OL} = 20 \text{ mA}$		0.3	0.5	V
ΙĮ	$V_{CC} = 0$,	V _I = 7 V			0.1	mA
lін	$V_{CC} = 5.5 \text{ V},$	V _I = 2.7 V			20	μΑ
I _{IL}	$V_{CC} = 5.5 \text{ V},$	V _I = 0.5 V			- 0.6	mA
l _{OS} ‡	$V_{CC} = 5.5 \text{ V},$	V _O = 0	- 60		- 150	mA
^I ССН	$V_{CC} = 5.5 \text{ V},$	See Note 2		55	72	mA
ICCL	$V_{CC} = 5.5 \text{ V},$	See Note 3		70	90	mA

[†] All typical values are at $V_{CC} = 5 \text{ V}$, $T_A = 25^{\circ}\text{C}$.

timing requirements

			V _{CC} :	= 5 V, 25°C	$V_{CC} = 4.5 \text{ V to } 5.5 \text{ V},$ $T_A = \text{MIN to MAX}$		UNIT		
			MIN	MAX	MIN	MAX	ĺ		
fclock	Clock frequency		0	110	0	110	MHz		
t _W	Pulse duration		4		5		ns		
t _{Su} Setup	Setup time before CLK↑	Data high or low	2		2		ns		
		CE high	2.5		2.5				
		CE low	4		4.5				
th		Data high or low	1		1		ns		
	Hold time after CLK↑	CE high or low	0		0				

[§] For conditions shown as MIN or MAX, use the appropriate value specified under recommended operating conditions.



[‡] Not more than one output should be shorted at a time, and the duration of the short circuit should not exceed one second.

NOTES: 2. I_{CCH} is measured after applying a momentary ground, then 4.5 V, to the clock input with all data inputs at 4.5 V and the enable input at GND

^{3.} I_{CCL} is measured after applying a momentary ground, then 4.5 V, to the clock input with all data and enable inputs at GND.

SN74F377A OCTAL D-TYPE FLIP-FLOP WITH CLOCK ENABLE SDFS018D – D2932, MARCH 1987 – REVISED OCTOBER 1993

switching characteristics (see Note 4)

PARAMETER	FROM (INPUT)	TO (OUTPUT)	C _L R _L	C = 5 V, = 50 pF = 500 Ω = 25°C	,	V _{CC} = 4.5 C _L = 50 pl R _L = 500 Ω T _A = MIN 1	2,	UNIT
f _{max}			110	125		110		MHz
t _{PLH}	CLK	Any Q	4	6.5	8.5	4	10	20
^t PHL		Ally Q	4	7	9	4	10.5	ns

[†] For conditions shown as MIN or MAX, use the appropriate value specified under recommended operating conditions. NOTE 4: Load circuit and waveforms are shown in Section 1.



IMPORTANT NOTICE

Texas Instruments and its subsidiaries (TI) reserve the right to make changes to their products or to discontinue any product or service without notice, and advise customers to obtain the latest version of relevant information to verify, before placing orders, that information being relied on is current and complete. All products are sold subject to the terms and conditions of sale supplied at the time of order acknowledgement, including those pertaining to warranty, patent infringement, and limitation of liability.

TI warrants performance of its semiconductor products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are utilized to the extent TI deems necessary to support this warranty. Specific testing of all parameters of each device is not necessarily performed, except those mandated by government requirements.

CERTAIN APPLICATIONS USING SEMICONDUCTOR PRODUCTS MAY INVOLVE POTENTIAL RISKS OF DEATH, PERSONAL INJURY, OR SEVERE PROPERTY OR ENVIRONMENTAL DAMAGE ("CRITICAL APPLICATIONS"). TI SEMICONDUCTOR PRODUCTS ARE NOT DESIGNED, AUTHORIZED, OR WARRANTED TO BE SUITABLE FOR USE IN LIFE-SUPPORT DEVICES OR SYSTEMS OR OTHER CRITICAL APPLICATIONS. INCLUSION OF TI PRODUCTS IN SUCH APPLICATIONS IS UNDERSTOOD TO BE FULLY AT THE CUSTOMER'S RISK.

In order to minimize risks associated with the customer's applications, adequate design and operating safeguards must be provided by the customer to minimize inherent or procedural hazards.

TI assumes no liability for applications assistance or customer product design. TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right of TI covering or relating to any combination, machine, or process in which such semiconductor products or services might be or are used. TI's publication of information regarding any third party's products or services does not constitute TI's approval, warranty or endorsement thereof.

Copyright © 1998, Texas Instruments Incorporated