
SCAS296N - JANUARY 1993 - REVISED AUGUST 2003


- Operate From 1.65 V to 3.6 V
- Inputs Accept Voltages to 5.5 V
- Max t<sub>pd</sub> of 6.5 ns at 3.3 V
- Typical V<sub>OLP</sub> (Output Ground Bounce) <0.8 V at  $V_{CC} = 3.3 \text{ V}, T_{\Delta} = 25^{\circ}\text{C}$
- Typical V<sub>OHV</sub> (Output V<sub>OH</sub> Undershoot) >2 V at  $V_{CC} = 3.3$  V,  $T_A = 25$ °C
- **Support Mixed-Mode Signal Operation on** All Ports (5-V Input/Output Voltage With 3.3-V V<sub>CC</sub>)

- Ioff Supports Partial-Power-Down Mode Operation
- Latch-Up Performance Exceeds 250 mA Per JESD 17
- **ESD Protection Exceeds JESD 22** 
  - 2000-V Human-Body Model (A114-A)
  - 200-V Machine Model (A115-A)
  - 1000-V Charged-Device Model (C101)


SN54LVC374A . . . J OR W PACKAGE SN74LVC374A . . . DB, DGV, DW, N, NS, **OR PW PACKAGE** (TOP VIEW)



SN74LVC374A . . . RGY PACKAGE (TOP VIEW)



SN54LVC374A . . . FK PACKAGE (TOP VIEW)



#### description/ordering information

The SN54LVC374A octal edge-triggered D-type flip-flop is designed for 2.7-V to 3.6-V V<sub>CC</sub> operation, and the SN74LVC374A octal edge-triggered D-type flip-flop is designed for 1.65-V to 3.6-V V<sub>CC</sub> operation.

These devices feature 3-state outputs designed specifically for driving highly capacitive or relatively low-impedance loads. These devices are particularly suitable for implementing buffer registers, input/output (I/O) ports, bidirectional bus drivers, and working registers.

On the positive transition of the clock (CLK) input, the Q outputs are set to the logic levels set up at the data (D) inputs.

A buffered output-enable (OE) input can be used to place the eight outputs in either a normal logic state (high or low logic levels) or the high-impedance state. In the high-impedance state, the outputs neither load nor drive the bus lines significantly. The high-impedance state and increased drive provide the capability to drive bus lines without interface or pullup components.

OE does not affect internal operations of the latch. Old data can be retained or new data can be entered while the outputs are in the high-impedance state.

Inputs can be driven from either 3.3-V or 5-V devices. This feature allows the use of these devices as translators in a mixed 3.3-V/5-V system environment.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.



SCAS296N - JANUARY 1993 - REVISED AUGUST 2003

#### description/ordering information (continued)

These devices are fully specified for partial-power-down applications using  $I_{\text{off}}$ . The  $I_{\text{off}}$  circuitry disables the outputs, preventing damaging current backflow through the devices when they are powered down.

To ensure the high-impedance state during power up or power down,  $\overline{\text{OE}}$  should be tied to  $V_{CC}$  through a pullup resistor; the minimum value of the resistor is determined by the current-sinking capability of the driver.

#### ORDERING INFORMATION


| TA             | PACK        | AGE <sup>†</sup> | ORDERABLE<br>PART NUMBER | TOP-SIDE MARKING |  |
|----------------|-------------|------------------|--------------------------|------------------|--|
|                | PDIP – N    | Tube of 20       | SN74LVC374AN             | SN74LVC374AN     |  |
| -40°C to 85°C  | QFN – RGY   | Reel of 1000     | SN74LVC374ARGYR          | LC374A           |  |
|                | 0010 011    | Tube of 25       | SN74LVC374ADW            | 11/00744         |  |
|                | SOIC - DW   | Reel of 2000     | SN74LVC374ADWR           | LVC374A          |  |
|                | SOP – NS    | Reel of 2000     | SN74LVC374ANSR           | LVC374A          |  |
|                | SSOP – DB   | Reel of 2000     | SN74LVC374ADBR           | LC374A           |  |
|                |             | Tube of 70       | SN74LVC374APW            |                  |  |
|                | TSSOP - PW  | Reel of 2000     | SN74LVC374APWR           | LC374A           |  |
|                |             | Reel of 250      | SN74LVC374APWT           | 1                |  |
|                | TVSOP – DGV | Reel of 2000     | SN74LVC374ADGVR          | LC374A           |  |
|                | CDIP – J    | Tube of 20       | SNJ54LVC374AJ            | SNJ54LVC374AJ    |  |
| –55°C to 125°C | CFP – W     | Tube of 85       | SNJ54LVC374AW            | SNJ54LVC374AW    |  |
|                | LCCC – FK   | Tube of 55       | SNJ54LVC374AFK           | SNJ54LVC374AFK   |  |

<sup>†</sup> Package drawings, standard packing quantities, thermal data, symbolization, and PCB design guidelines are available at www.ti.com/sc/package.

# FUNCTION TABLE (each flip-flop)

|    | INPUTS     |   | OUTPUT         |
|----|------------|---|----------------|
| OE | CLK        | D | Q              |
| L  | 1          | Н | Н              |
| L  | $\uparrow$ | L | L              |
| L  | H or L     | Χ | Q <sub>0</sub> |
| Н  | Χ          | Χ | Z              |

#### logic diagram (positive logic)



TEXAS INSTRUMENTS

SCAS296N - JANUARY 1993 - REVISED AUGUST 2003

### absolute maximum ratings over operating free-air temperature range (unless otherwise noted)†

| Supply voltage range, V <sub>CC</sub>  |                                    |
|--|------------------------------------|
| Voltage range applied to any output in the high-impedance or power-off state, V <sub>O</sub> | 0.0 v to 0.0 v                     |
| (see Note 1)   | 0.5 V to 6.5 V                     |
| Voltage range applied to any output in the high or low state, VO                             |                                    |
| (see Notes 1 and 2)  | $0.5$ V to $V_{CC}$ + $0.5$ V      |
| Input clamp current, $I_{IK}$ ( $V_I < 0$ )  | –50 mA                             |
| Output clamp current, I <sub>OK</sub> (V <sub>O</sub> < 0)                                   |                                    |
| Continuous output current, IO  |                                    |
| Continuous current through V <sub>CC</sub> or GND  |                                    |
| Package thermal impedance, θ <sub>JA</sub> (see Note 3): DB package                          | 70°C/W                             |
| (see Note 3): DGV package  |                                    |
| (see Note 3): DW package   |                                    |
| (see Note 3): N package  |                                    |
| (see Note 3): NS package   |                                    |
| (see Note 3): PW package   |                                    |
| (see Note 4): RGY package  |                                    |
| Storage temperature range, T <sub>stq</sub>  | $-65^{\circ}$ C to $150^{\circ}$ C |

<sup>†</sup> Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

NOTES: 1. The input negative-voltage and output voltage ratings may be exceeded if the input and output current ratings are observed.

- 2. The value of V<sub>CC</sub> is provided in the recommended operating conditions table.
- 3. The package thermal impedance is calculated in accordance with JESD 51-7.
- 4. The package thermal impedance is calculated in accordance with JESD 51-5.



# SN54LVC374A, SN74LVC374A OCTAL EDGE-TRIGGERED D-TYPE FLIP-FLOPS WITH 3-STATE OUTPUTS SCAS296N - JANUARY 1993 - REVISED AUGUST 2003

#### recommended operating conditions (see Note 5)

|                 |                                    |  | SN54LV | C374A | SN74L                  | VC374A                 |      |  |
|-----------------|------------------------------------|--|--------|-------|------------------------|------------------------|------|--|
|                 |                                    |  | MIN    | MAX   | MIN                    | MAX                    | UNIT |  |
| .,              | 0 1 1                              | Operating                                  | 2      | 3.6   | 1.65                   | 3.6                    | .,   |  |
| VCC             | Supply voltage                     | Data retention only                        | 1.5    |       | 1.5                    |                        | V    |  |
|                 |                                    | V <sub>CC</sub> = 1.65 V to 1.95 V         |        |       | 0.65 × V <sub>CC</sub> |                        |      |  |
| $V_{IH}$        | High-level input voltage           | $V_{CC} = 2.3 \text{ V to } 2.7 \text{ V}$ |        |       | 1.7                    |                        | V    |  |
|                 |                                    | V <sub>CC</sub> = 2.7 V to 3.6 V           | 2      |       | 2                      |                        |      |  |
|                 |                                    | V <sub>CC</sub> = 1.65 V to 1.95 V         |        |       |                        | 0.35 × V <sub>CC</sub> |      |  |
| ٧ <sub>IL</sub> | Low-level input voltage            | V <sub>CC</sub> = 2.3 V to 2.7 V           |        |       |                        | 0.7                    | V    |  |
|                 |                                    | V <sub>CC</sub> = 2.7 V to 3.6 V           |        | 0.8   |                        | 0.8                    |      |  |
| ٧ <sub>I</sub>  | Input voltage                      |  | 0      | 5.5   | 0                      | 5.5                    | V    |  |
| .,              | 0 !:                               | High or low state                          | 0      | Vcc   | 0                      | Vcc                    | V    |  |
| VO              | Output voltage                     | 3-state                                    | 0      | 5.5   | 0                      | 5.5                    |      |  |
|                 |                                    | V <sub>CC</sub> = 1.65 V                   |        |       |                        | -4                     |      |  |
|                 |                                    | V <sub>CC</sub> = 2.3 V                    |        |       |                        | -8                     |      |  |
| lOH             | High-level output current          | V <sub>CC</sub> = 2.7 V                    |        | -12   |                        | -12                    | mA   |  |
|                 |                                    | V <sub>CC</sub> = 3 V                      |        | -24   |                        | -24                    |      |  |
|                 |                                    | V <sub>CC</sub> = 1.65 V                   |        |       |                        | 4                      |      |  |
|                 |                                    | V <sub>CC</sub> = 2.3 V                    |        |       |                        | 8                      |      |  |
| IOL             | Low-level output current           | V <sub>CC</sub> = 2.7 V                    |        | 12    |                        | 12                     | mA   |  |
|                 |                                    | V <sub>CC</sub> = 3 V                      |        | 24    |                        | 24                     |      |  |
| Δt/Δν           | Input transition rise or fall rate |  |        | 10    |                        | 10                     | ns/V |  |
| TA              | Operating free-air temperature     |  | -55    | 125   | -40                    | 85                     | °C   |  |

NOTE 5: All unused inputs of the device must be held at  $V_{CC}$  or GND to ensure proper device operation. Refer to the TI application report, Implications of Slow or Floating CMOS Inputs, literature number SCBA004.



SCAS296N - JANUARY 1993 - REVISED AUGUST 2003

#### electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

| VOH  VOL  II  Ioff IOZ ICC  ΔICC |   |                 | SN54                 | LVC374 | Δ.   | SN74                 | LVC374A    | A    |      |  |
|----------------------------------|---|-----------------|----------------------|--------|------|----------------------|------------|------|------|--|
| PARAMETER                        | TEST CONDITIONS   | VCC             | MIN                  | TYP†   | MAX  | MIN                  | TYP†       | MAX  | UNIT |  |
|                                  | 100 110   | 1.65 V to 3.6 V |                      |        |      | V <sub>CC</sub> -0.2 |            |      |      |  |
|                                  | I <sub>OH</sub> = -100 μA   | 2.7 V to 3.6 V  | V <sub>CC</sub> -0.2 |        |      |                      |            |      |      |  |
|                                  | $I_{OH} = -4 \text{ mA}$  | 1.65 V          |                      |        |      | 1.2                  |            |      |      |  |
| Voн                              | $I_{OH} = -8 \text{ mA}$  | 2.3 V           |                      |        |      | 1.7                  |            |      | V    |  |
|                                  | 104   | 2.7 V           | 2.2                  |        |      | 2.2                  |            |      |      |  |
|                                  | $I_{OH} = -12 \text{ mA}$   | 3 V             | 2.4                  |        |      | 2.4                  |            |      |      |  |
|                                  | I <sub>OH</sub> = -24 mA  | 3 V             | 2.2                  |        |      | 2.2                  |            |      |      |  |
|                                  | 1 400 4   | 1.65 V to 3.6 V |                      |        |      |                      |            | 0.2  |      |  |
|                                  | $I_{OL} = 100 \mu\text{A}$  | 2.7 V to 3.6 V  |                      |        | 0.2  |                      |            |      |      |  |
| V                                | I <sub>OL</sub> = 4 mA  | 1.65 V          |                      |        |      |                      |            | 0.45 | V    |  |
| VOL                              | I <sub>OL</sub> = 8 mA  | 2.3 V           |                      |        |      |                      |            | 0.7  | V    |  |
|                                  | I <sub>OL</sub> = 12 mA   | 2.7 V           |                      |        | 0.4  |                      | 0.7<br>0.4 | 0.4  |      |  |
|                                  | I <sub>OL</sub> = 24 mA   | 3 V             |                      |        | 0.55 |                      |            | 0.55 |      |  |
| lį                               | V <sub>I</sub> = 0 to 5.5 V   | 3.6 V           |                      |        | ±5   |                      |            | ±5   | μΑ   |  |
| l <sub>off</sub>                 | $V_I$ or $V_O = 5.5 V$  | 0               |                      |        |      |                      |            | ±10  | μΑ   |  |
| loz                              | V <sub>O</sub> = 0 to 5.5 V   | 3.6 V           |                      |        | ±15  |                      |            | ±10  | μΑ   |  |
|                                  | V <sub>I</sub> = V <sub>CC</sub> or GND   | 0.014           |                      |        | 10   |                      |            | 10   |      |  |
| ICC                              | $3.6 \text{ V} \le \text{V}_{\text{I}} \le 5.5 \text{ V}^{\ddagger}$ $I_{\text{O}} = 0$ | 3.6 V           |                      |        | 10   |                      |            | 10   | μΑ   |  |
| ΔICC                             | One input at V <sub>CC</sub> – 0.6 V,<br>Other inputs at V <sub>CC</sub> or GND         | 2.7 V to 3.6 V  |                      |        | 500  |                      |            | 500  | μΑ   |  |
| Ci                               | V <sub>I</sub> = V <sub>CC</sub> or GND   | 3.3 V           |                      | 4      | 12   |                      | 4          | ·    | pF   |  |
| Co                               | $V_O = V_{CC}$ or GND   | 3.3 V           |                      | 5.5    | 12   |                      | 5.5        |      | pF   |  |

<sup>†</sup> All typical values are at  $V_{CC}$  = 3.3 V,  $T_A$  = 25°C. ‡ This applies in the disabled state only.

# timing requirements over recommended operating free-air temperature range (unless otherwise noted) (see Figure 1)

|                 |                                 |                         | SN54LV | C374A                              |     |      |
|-----------------|---------------------------------|-------------------------|--------|------------------------------------|-----|------|
|                 |                                 | V <sub>CC</sub> = 2.7 V |        | V <sub>CC</sub> = 3.3 V<br>± 0.3 V |     | UNIT |
|                 |                                 | MIN                     | MAX    | MIN                                | MAX |      |
| fclock          | Clock frequency                 |                         | 80     |                                    | 100 | MHz  |
| t <sub>W</sub>  | Pulse duration, CLK high or low | 3.3                     |        | 3.3                                |     | ns   |
| t <sub>su</sub> | Setup time, data before CLK↑    | 2                       |        | 2                                  |     | ns   |
| th              | Hold time, data after CLK↑      | 1.5                     |        | 1.5                                |     | ns   |

SCAS296N - JANUARY 1993 - REVISED AUGUST 2003

# timing requirements over recommended operating free-air temperature range (unless otherwise noted) (see Figure 1)

|                 |                                 |                   |     |                   | SN74LV | /C374A                  | 374A |                                    |     |      |  |
|-----------------|---------------------------------|-------------------|-----|-------------------|--------|-------------------------|------|------------------------------------|-----|------|--|
|                 |                                 | V <sub>CC</sub> = |     | V <sub>CC</sub> = |        | V <sub>CC</sub> = 2.7 V |      | V <sub>CC</sub> = 3.3 V<br>± 0.3 V |     | UNIT |  |
|                 |                                 | MIN               | MAX | MIN               | MAX    | MIN                     | MAX  | MIN                                | MAX |      |  |
| fclock          | Clock frequency                 |                   | †   |                   | †      |                         | 80   |                                    | 100 | MHz  |  |
| t <sub>W</sub>  | Pulse duration, CLK high or low | †                 |     | †                 |        | 3.3                     |      | 3.3                                |     | ns   |  |
| t <sub>su</sub> | Setup time, data before CLK↑    | †                 |     | †                 |        | 2                       |      | 2                                  |     | ns   |  |
| th              | Hold time, data after CLK↑      | †                 |     | †                 |        | 1.5                     |      | 1.5                                |     | ns   |  |

<sup>†</sup> This information was not available at the time of publication.

# switching characteristics over recommended operating free-air temperature range (unless otherwise noted) (see Figure 1)

|                  |                 |                |                         | SN54LV | /C374A                             |     |      |
|------------------|-----------------|----------------|-------------------------|--------|------------------------------------|-----|------|
| PARAMETER        | FROM<br>(INPUT) | TO<br>(OUTPUT) | V <sub>CC</sub> = 2.7 V |        | V <sub>CC</sub> = 3.3 V<br>± 0.3 V |     | UNIT |
|                  |                 |                | MIN                     | MAX    | MIN                                | MAX |      |
| f <sub>max</sub> |                 |                | 80                      |        | 100                                |     | MHz  |
| <sup>t</sup> pd  | CLK             | Q              |                         | 9.5    | 1                                  | 8.5 | ns   |
| t <sub>en</sub>  | ŌE              | Q              |                         | 9.5    | 1                                  | 8.5 | ns   |
| <sup>t</sup> dis | ŌE              | Q              |                         | 8      | 1                                  | 7   | ns   |

# switching characteristics over recommended operating free-air temperature range (unless otherwise noted) (see Figure 1)

|                    |                 |                |                                     |     |                                    | SN74LV | /C374A                  |     |                                    |     |      |  |  |  |
|--------------------|-----------------|----------------|-------------------------------------|-----|------------------------------------|--------|-------------------------|-----|------------------------------------|-----|------|--|--|--|
| PARAMETER          | FROM<br>(INPUT) | TO<br>(OUTPUT) | V <sub>CC</sub> = 1.8 V<br>± 0.15 V |     | V <sub>CC</sub> = 2.5 V<br>± 0.2 V |        | V <sub>CC</sub> = 2.7 V |     | V <sub>CC</sub> = 3.3 V<br>± 0.3 V |     | UNIT |  |  |  |
|                    |                 |                | MIN                                 | MAX | MIN                                | MAX    | MIN                     | MAX | MIN                                | MAX |      |  |  |  |
| fmax               |                 |                | †                                   |     | †                                  |        | 80                      |     | 100                                |     | MHz  |  |  |  |
| <sup>t</sup> pd    | CLK             | Q              | †                                   | †   | †                                  | †      |                         | 8.1 | 1.5                                | 7   | ns   |  |  |  |
| <sup>t</sup> en    | OE              | Q              | †                                   | †   | †                                  | †      |                         | 8.5 | 1.5                                | 7.5 | ns   |  |  |  |
| <sup>t</sup> dis   | ŌE              | Q              | †                                   | †   | †                                  | †      |                         | 7.1 | 1.5                                | 6.5 | ns   |  |  |  |
| <sup>t</sup> sk(o) |                 |                |                                     |     |                                    |        |                         |     |                                    | 1   | ns   |  |  |  |

<sup>&</sup>lt;sup>†</sup> This information was not available at the time of publication.

### operating characteristics, T<sub>A</sub> = 25°C


| PARAMETER |                               | TEST             | V <sub>CC</sub> = 1.8 V | V <sub>CC</sub> = 2.5 V | V <sub>CC</sub> = 3.3 V | UNIT |      |
|-----------|-------------------------------|------------------|-------------------------|-------------------------|-------------------------|------|------|
|           | TAKAMETEK                     | COI              |                         | TYP                     | TYP                     | TYP  | ONIT |
| Cpo       | Power dissipation capacitance | Outputs enabled  | f = 10 MHz              | †                       | †                       | 54.5 | pF   |
| Opt       | per flip-flop                 | Outputs disabled | 1 = 10 MH2              | †                       | †                       | 13.5 | рг   |

<sup>&</sup>lt;sup>†</sup> This information was not available at the time of publication.




SCAS296N - JANUARY 1993 - REVISED AUGUST 2003

#### PARAMETER MEASUREMENT INFORMATION



| TEST      | S1    |
|-----------|-------|
| tPLH/tPHL | Open  |
| tPLZ/tPZL | VLOAD |
| tPHZ/tPZH | GND   |

| .,                | INF            | PUTS                           |                    |                   | •     | _            | .,         |
|-------------------|----------------|--------------------------------|--------------------|-------------------|-------|--------------|------------|
| Vcc               | ٧ <sub>I</sub> | t <sub>r</sub> /t <sub>f</sub> | VM                 | VLOAD             | CL    | RL           | $V_\Delta$ |
| 1.8 V ± 0.15 V    | VCC            | ≤2 ns                          | V <sub>CC</sub> /2 | 2×V <sub>CC</sub> | 30 pF | <b>1 k</b> Ω | 0.15 V     |
| 2.5 V $\pm$ 0.2 V | VCC            | ≤2 ns                          | V <sub>CC</sub> /2 | 2×V <sub>CC</sub> | 30 pF | 500 $\Omega$ | 0.15 V     |
| 2.7 V             | 2.7 V          | ≤2.5 ns                        | 1.5 V              | 6 V               | 50 pF | 500 $\Omega$ | 0.3 V      |
| 3.3 V $\pm$ 0.3 V | 2.7 V          | ≤2.5 ns                        | 1.5 V              | 6 V               | 50 pF | <b>500</b> Ω | 0.3 V      |



- NOTES: A. C<sub>I</sub> includes probe and jig capacitance.
  - B. Waveform 1 is for an output with internal conditions such that the output is low except when disabled by the output control. Waveform 2 is for an output with internal conditions such that the output is high except when disabled by the output control.
  - C. All input pulses are supplied by generators having the following characteristics: PRR  $\leq$  10 MHz, Z<sub>O</sub> = 50  $\Omega$ .
  - D. The outputs are measured one at a time with one transition per measurement.
  - E. tpLz and tpHz are the same as tdis.
  - F. tpzL and tpzH are the same as ten.
  - G. tpLH and tpHL are the same as tpd.
  - H. All parameters and waveforms are not applicable to all devices.

Figure 1. Load Circuit and Voltage Waveforms



#### 14 LEADS SHOWN




NOTES:

- A. All linear dimensions are in inches (millimeters).
- B. This drawing is subject to change without notice.
- C. This package is hermetically sealed with a ceramic lid using glass frit.
- D. Index point is provided on cap for terminal identification only on press ceramic glass frit seal only.
- E. Falls within MIL STD 1835 GDIP1-T14, GDIP1-T16, GDIP1-T18 and GDIP1-T20.

#### W (R-GDFP-F20)

#### **CERAMIC DUAL FLATPACK**



NOTES: A. All linear dimensions are in inches (millimeters).

- B. This drawing is subject to change without notice.
- C. This package can be hermetically sealed with a ceramic lid using glass frit.
- D. Index point is provided on cap for terminal identification only.
- E. Falls within Mil-Std 1835 GDFP2-F20

#### FK (S-CQCC-N\*\*)

#### **28 TERMINAL SHOWN**

#### **LEADLESS CERAMIC CHIP CARRIER**



NOTES: A. All linear dimensions are in inches (millimeters).


- B. This drawing is subject to change without notice.
- C. This package can be hermetically sealed with a metal lid.
- D. The terminals are gold plated.
- E. Falls within JEDEC MS-004



#### N (R-PDIP-T\*\*)

#### **16 PINS SHOWN**

#### PLASTIC DUAL-IN-LINE PACKAGE



NOTES: A. All linear dimensions are in inches (millimeters).

B. This drawing is subject to change without notice.

Falls within JEDEC MS-001, except 18 and 20 pin minimum body Irngth (Dim A).

The 20 pin end lead shoulder width is a vendor option, either half or full width.

#### DGV (R-PDSO-G\*\*)

#### **24 PINS SHOWN**

#### **PLASTIC SMALL-OUTLINE**




NOTES: A. All linear dimensions are in millimeters.

B. This drawing is subject to change without notice.

C. Body dimensions do not include mold flash or protrusion, not to exceed 0,15 per side.

D. Falls within JEDEC: 24/48 Pins – MO-153 14/16/20/56 Pins – MO-194





NOTES:


- A. All linear dimensions are in millimeters.
- B. This drawing is subject to change without notice.
- C. QFN (Quad Flatpack No-Lead) package configuration.
- The package thermal performance may be enhanced by bonding the thermal die pad to an external thermal plane. This pad is electrically and thermally connected to the backside of the die and possibly selected ground leads.
- E. Package complies to JEDEC MO-241 variation BC.



#### DW (R-PDSO-G\*\*)

#### PLASTIC SMALL-OUTLINE PACKAGE

#### **16 PINS SHOWN**



NOTES: A. All linear dimensions are in inches (millimeters).

B. This drawing is subject to change without notice.

C. Body dimensions do not include mold flash or protrusion not to exceed 0.006 (0,15).

D. Falls within JEDEC MS-013

#### **MECHANICAL DATA**

### NS (R-PDSO-G\*\*)

## 14-PINS SHOWN

#### PLASTIC SMALL-OUTLINE PACKAGE



NOTES:

- A. All linear dimensions are in millimeters.
- B. This drawing is subject to change without notice.
- C. Body dimensions do not include mold flash or protrusion, not to exceed 0,15.



#### DB (R-PDSO-G\*\*)

#### PLASTIC SMALL-OUTLINE

#### **28 PINS SHOWN**



NOTES: A. All linear dimensions are in millimeters.

B. This drawing is subject to change without notice.

C. Body dimensions do not include mold flash or protrusion not to exceed 0,15.

D. Falls within JEDEC MO-150

#### PW (R-PDSO-G\*\*)

#### 14 PINS SHOWN

#### PLASTIC SMALL-OUTLINE PACKAGE



NOTES: A. All linear dimensions are in millimeters.

B. This drawing is subject to change without notice.

C. Body dimensions do not include mold flash or protrusion not to exceed 0,15.

D. Falls within JEDEC MO-153

#### **IMPORTANT NOTICE**

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

| Products         |                        | Applications       |                           |
|------------------|------------------------|--------------------|---------------------------|
| Amplifiers       | amplifier.ti.com       | Audio              | www.ti.com/audio          |
| Data Converters  | dataconverter.ti.com   | Automotive         | www.ti.com/automotive     |
| DSP              | dsp.ti.com             | Broadband          | www.ti.com/broadband      |
| Interface        | interface.ti.com       | Digital Control    | www.ti.com/digitalcontrol |
| Logic            | logic.ti.com           | Military           | www.ti.com/military       |
| Power Mgmt       | power.ti.com           | Optical Networking | www.ti.com/opticalnetwork |
| Microcontrollers | microcontroller.ti.com | Security           | www.ti.com/security       |
|                  |                        | Telephony          | www.ti.com/telephony      |
|                  |                        | Video & Imaging    | www.ti.com/video          |
|                  |                        | Wireless           | www.ti.com/wireless       |

Mailing Address: Texas Instruments

Post Office Box 655303 Dallas, Texas 75265

Copyright © 2003, Texas Instruments Incorporated